



Wandler 100V Adapter ELA auf Cinch 2Kanal



75,00 € *

* Preise inkl. gesetzlicher MwSt. zzgl. Versandkosten

Marke: APart Audio
Bestell-Nr.: 43-890-05004

Pegelhändler
2-Kanal (Stereo)



ELA Adapter 100V Wandler auch Cinch

Universal 2-Kanal (Stereo) Input Adapter mit Ground-Loop Isolator

- Für den Anschluss einer 100-V-Audiosignal-Quelle an Geräte mit Line-Eingang
- 100V Eingang mit Schraub-Steckklemme
- Ein- und Ausgang galvanisch getrennt
- Stereo bzw. 2-Kanal Cinch-Ausgang, unsymmetrisch
- der Input Level ist umstellbar (High/Line/Tel)
- Solides Metallgehäuse
- Keine Spannungsversorgung über Netzteil oder Batterie notwendig
- 2 Kanal Eingänge wie folgt:
 - A) ELA: 33V - 50 - 100 V
 - B) PA Amp Input 4-8ohm Input Balanced über Schraubklemme
 - 5W...120W...600W..max. 1000W Input von PA Verstärker
 - C) Stereo-Cinchbuchsen
- 2 Kanal Ausgänge wie folgt:
 - A) Stereo-Cinch
 - B) Output Balanced über Schraubklemme
- Abmessungen: 241 x 72 x 44mm
- Gewicht: 500g

The APart BUZZSTOP-MKIII is a universal input adaptor that can be used for all connections and extensions. The input level selector allows you to convert any amplifier output to any line-level output, balanced or unbalanced. (E.g.: You can convert a 100V loudspeaker signal into a balanced or unbalanced line level signal).

The BUZZSTOP-MKIII also makes it possible to convert an unbalanced signal into balanced and vice versa.